

# SATA 3 to M.2 SSD RAID Enclosure Assembly Guide










## Features

- Standard 2.5", 9.5mm(H) Form Factor
- Support a SATA host & two M.2 NGFF SSD devices
- Built-in ASM1092R high performance processor
- RAID mode switch by hardware strapping or GUI controller
- RAID mode: RAID 0(fast) / RAID 1(safe) / JBOD(volume)
- 3-button Hardware switch to setup RAID mode
- Green LED indicate SATA 3 host active
- Red LED indicate M.2 NGFF SSD error


## Before Assembly

- Please read through the installation guide first.
- Please check the accessory list before the integration. Contact your local distributor if you find any parts missing.
- Please retain the original package if you need to return the package for RMA.

## Assembling Accessories



		
M3x3 Screw*1	M3x5 Screw*1	M3 Nut*1
		
Copper Nut H: 1.45mm*1	(for Adapter) M2x3 Screw*5	(for Housing) M2x3 Screw*5
		
2.5" Housing (9.5H) *1	Adapter*1	
<b>Required Tools (Not included)</b> All you need to assemble this unit are one screwdriver. 		

## Assembly



**STEP 1.  
Make M.2 SSD Stand**  
Put copper nut on the same side of the M.2 connector.  
Fix with M3x5mm screw from bottom to top of the adapter.

**STEP 2.  
Insert M.2 SSD**  
Insert M.2 SSD into M.2 67pin connector.  
Press down M.2 SSD and aim to the copper nut hole.





**STEP 3.  
Fix M.2 SSD**  
Use M3 nuts to fix M.2 NGFF SSD on the adapter, namely complete the assembly.

**Repeat Step 1~3 for the 2nd M.2 (NGFF) SSD.**

If your M.2 SSD is 2280 form factor, pls ignore STEP 1~3.  
Use M3x3 Screws 2pcs to fix M.2 NGFF SSD directly.

**STEP 4.  
Fix Adapter & Housing**  
Assembly the adapter into 2.5" housing with 4pcs of M2x3 screws.




**STEP 5.  
Combine 2.5" Housing**  
Cover the Top cover.  
Use 4pcs of M2x3 screws to fix the housing from broadsides.

## RAID mode setup :

- Set RAID mode, you must install both 2 devices; otherwise, it is impossible to set RAID mode.

### Set RAID 0 mode :



1	2	3
ON	ON	OFF

Switch SW2 as ON-ON-OFF.  
Push SW1 Button to complete the setup.

Start PC, BIOS should show RAID 0 mode (ASMT109-Fast).

### Set RAID 1 mode :




1	2	3
ON	OFF	ON

Switch SW2 as ON-OFF-ON.  
Push SW1 Button to complete the setup.

Start PC, BIOS should show RAID 1 mode (ASMT109-Safe).

### Set JBOD mode :



1	2	3
ON	ON	ON

Switch SW2 as ON-ON-ON.  
Push SW1 Button to complete the setup.

Start PC, BIOS should show JBOD mode (ASMT109-Volume).